

HEROTEK, INC.

155 Baytech Drive
San Jose, CA 95134-2303
www.herotek.com
e-mail: info@herotek.com



Comb Generator Models Listed Below in Stock for Immediate Delivery.

Consult factory for more details.

Model	Input Freq (MHz)	Input Power (dBm)	Max Input VSWR	Min Output Power per Picket (dBm)				Outline
				Up to 4 GHz	4-8 GHz	8-12.4 GHz	12.4-18 GHz	
GC100RC	100	27	2:1	-10	-20	-30	-40	C
GC100RL	100	27	2:1	-10	-20	-30	-40	L
GCA100A*	100	0	2:1	-12	-20	-30	-40	3A
GCA100B*	100	+10	2:1	-12	-20	-30	-40	3A
GC200RC	200	27	2:1	-5	-15	-25	-35	C
GC200RL	200	27	2:1	-5	-15	-25	-35	L
GC250RC	250	27	2:1	0	-10	-20	-30	C
GC500RC	500	27	2:1	+5	-5	-15	-20	C
GCA500A	500	0	2:1	+3	-5	-15	-20	3A
GCA500B	500	+10	2:1	+3	-5	-15	-20	1A
GC1000RC	1000	27	2:1	+5	0	-10	-15	C
GCA1000A*	1000	0	2:1	+3	0	-10	-15	3A
GCA1000B*	1000	+10	2:1	+3	0	-10	-15	1A

*With Integrated Pre-Amplifier